

SECONDARY CURRENT INJECTION TEST SET

RNT-5

Quality | Accuracy | Reliability



This is a Portable Testing Kit in One Unit, Suitable for Testing Protective Relay, Over Current Relay, Earth Fault Relay, Protective Device, Circuit Breaker, Tripping Coils etc. The set is Designed for Both Laboratory and field use.

TECHNICAL FEATURES

INPUT	230 Volts, single phase, 50Hz. AC.
OUTPUTS	<p>> Current Output</p> <ol style="list-style-type: none"> 1) 0-1 Amp. At 4/10 Volts. 2) 0-2 Amp. At 4/10 Volts. 3) 0-5 Amps. At 4/10 Volts. 4) 0-10 Amps. At 4/10 Volts. 5) 0-20 Amps. At 4/10 Volts. 6) 0-50 Amps. At 4 Volts. 7) 0-100 Amps. At 4 Volts. 8) 0-200 Amps. At 4 Volts. <p>Current Output is Continuously Variable & the Output is taken out Through a Multi Range C. T. The Secondary is Connected to an Ammeter Scaled in 0 to 100%.</p>
2) AC Voltage Output	Continuously variable 0-230V AC. Capacity-460VA.(Max).
3) Fixed AC Voltage	50V & 10V
4) Time Measurement	0-9.999Secs. & 0-99.99Secs. in two ranges.
Accuracy	1%
CURRENT CIRCUIT:	
Loading Transformer:	Double winding loading transformer of suitable burden to provided corresponding to the current output specified.
Mesuring CT	Multi ratio wound primary current transformer

Ratio	1-2-5-10-20-50-100-200A/5A.
Variable auto transformer	For smooth variation of current output at various ranges selected.
Metering	Digital meter. Basic Range - 0 to 5A AC. Scaled in 0 to 100% for all selected range. Accuracy - 1.5% of full range.
VOLTAGE CIRCUIT	One AC Voltmeter is provided for measuring the variable output AC voltage.
Timer Circuit Ranges	Dual range digital time interval meter I) 0-9.999 Sec. II) 0-99.99 Sec. in tow switchable ranges.
<p>Selector for NO & NC contacts. Reset push button. "Start" time signal is potential free closing or opening of auxiliary contacts of the set contactors.</p>	
GENERAL ARRAGEMENT	<p>The test kit will be in one unit. Meters, terminals, indicators, regulator knobs, timer display etc. will be fitted on the horizontal panel of the set which can be approached by opening the top lid. An input chord of 2 meter length with 3pin plug will be provided. loading transformer, measuring CT & protection circuit will be housed within the same unit.</p> <p>Operation manual, schematic circuit diagram work test report, warranty certificate will be supplied along with the set.</p>

Product Specifications are subject to change without notice

Manufactured By :

NEUTRONICS MANUFACTURING CO.

12-A, JOY COMPOUND, MAROL MAROSHI ROAD,
ANDHERI (E), MUMBAI - 400059.

TEL: 022-2925 0745 / 2920 1296. MOB: 98194 50890 / 98190 70556.

Email: sales@neutronics.co.in / bhavin_nmc@yahoo.com / mehul@neutronics.co.in

www.neutronics.co.in / www.neutronics.in

Marketed By: